

CPS-1250 Energy Storage Inverter

The world's most advanced utility-scale energy storage inverter

Featuring a highly efficient three level topology, the CPS-1250 inverter is purpose-built for energy storage applications, providing the perfect balance of performance, reliability, and cost-effectiveness.

The CPS-1250 is a 585kVA to 1336kVA bidirectional four quadrant capable converter. Available in outdoor or indoor-rated configurations, units can be paralleled for project size scaling to meet the needs of any grid-tied or microgrid application.

Capable of connecting to an 800VAC 3 phase grid connection, the CPS-1250 offers industry-leading power density and efficiency. The CPS-1250 allows DC input configuration flexibility to enable large duration battery connections or reduce balance of system costs through input consolidation.

The CPS-1250 inverter contains all required protective features, including an AC output breaker and DC pre-charge. This creates a cost savings compared to other inverters that require additional items for battery integration.



System Advantages:

- Seamless transfer from grid-tied to stand-alone mode with patented Dynamic Transfer feature
- Scalable to any grid-tied or microgrid application with paralleled units
- Cost savings by eliminating additional purchase of protective features
- Certified to UL 1741 Ed. 3, including SB smart inverter requirements

Key Technologies

- Islanded Operation (UF Mode)
- Dynamic Transfer
- Black Start (In-Rush Current Handling in UF Mode)
- Frequency Compensation Mode (F-Comp)
- VAR Compensation Mode (E-Comp)
- AC Current Limiting
- LVRT with Active Current Injection
- Multiple Parallel Inverter Microgrid Mode

TECHNICAL SPECIFICATIONS

Electrical

AC Input Voltage:	800V _{AC} / 690V _{AC} / 660V _{AC} / 630V _{AC} / 600V _{AC} / 540V _{AC} / 480V _{AC} / 415V _{AC} / 350V _{AC}
Grid Frequency:	60 Hz
Maximum Apparent Power:	1336 kVA (@ 800V _{AC}) 1152 kVA (@ 690V _{AC}) 1102 kVA (@ 660V _{AC}) 1052 kVA (@ 630V _{AC}) 1002 kVA (@ 600V _{AC}) 902 kVA (@ 540V _{AC}) 802 kVA (@ 480V _{AC}) 693 kVA (@ 415V _{AC}) 585 kVA (@ 350V _{AC})
Maximum Real Power:	1336 KW (@ 800V _{AC}) 1152 KW (@ 690V _{AC}) 1102 KW (@ 660V _{AC}) 1052 KW (@ 630V _{AC}) 1002 KW (@ 600V _{AC}) 902 KW (@ 540V _{AC}) 802 KW (@ 480V _{AC}) 693 KW (@ 415V _{AC}) 585 KW (@ 350V _{AC})
Maximum AC Current:	964ARMS
DC Voltage Range:	511-1500V _{DC} (@350-800V _{AC})
Maximum DC Current:	1170 _{ADC}
Power Factor:	Four Quadrant
Current Harmonics:	IEEE 1547 Compliant, <5% TDD
Maximum Efficiency:	98.58 @1500V _{DC} & 98.70 @1280V _{DC}

Environmental

Operating Temp:	-30 to +60°C, De-rated above +45°C
Max Elevation:	1000 Meters Full Power Up to 3000 Meters with De-rating
Cooling:	Forced Air Cooled
Enclosure:	NEMA 3R/IP 54
Dimensions (HxWxD):	79.72" x 49.0" x 43.3"
Weight:	2,205lbs

Certifications & Standards Compliance

UL1741 Ed. 3
IEEE 1547
CSA 22.2 #107.1
IEEE 519

Hardware Protections

AC Breaker with Shunt Trip
AC Surge Protection
DC Input Fuses
DC Pre-Charge

Software Protections

Battery Voltage and Current Curtail Limits to Protect Battery
AC Current Limiting Pending
DC Over/Under Voltage, Over Current Faults
AC Over/Under Voltage, Over/Under Frequency, Over Current Faults
Anti-islanding Protection (Open Phase at Inverter Terminals)
Temperature Monitoring and Protective Power Curtailment



Datasheets provided by Sensata Technologies, Inc., its subsidiaries and/or affiliates ("Sensata") are solely intended to assist third parties ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, valuation, and judgment in designing Buyer's systems and products. Sensata datasheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular datasheet. Sensata may make corrections, enhancements, improvements, and other changes to its datasheets or components without notice.

Buyers are authorized to use Sensata datasheets with the Sensata component(s) identified in each particular datasheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATASHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATASHEETS OR USE OF THE DATASHEETS, EXPRESS, IMPLIED, OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATASHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com. SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY, AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA. Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA



REGIONAL HEAD OFFICES

United States of America

Sensata Technologies
Attleboro, MA
Phone: 508-236-3800
E-mail: support@sensata.com

Netherlands

Sensata Technologies Holland B.V.
Hengelo
Phone: +31 74 357 8000
E-mail: support@sensata.com

China

Sensata Technologies China Co., Ltd.
Shanghai
Phone: +8621 2306 1500
E-mail: support@sensata.com

Copyright © 2023
Sensata Technologies, Inc.



85 Meadowland Drive, South Burlington, Vermont USA 05403

1.802.860.7200 | sales@dynapower.com

dynapower.com

