

## MPS-125 Energy Storage Inverter

# The world's most capable microgrid inverter

**This bi-directional 125kW energy storage inverter is transformer-less, air-cooled, and compact, and optimized for behind-the-meter energy storage applications.**

Featuring a highly efficient three-level topology, the MPS-125 is easily integrated into customer supplied battery storage systems. Multiple MPS-125 energy storage inverters can be paralleled together to scale to meet the needs of any behind-the-meter energy storage installation.

With all the functional capabilities of the grid-scale CPS inverter family, the MPS-125 supports frequency, voltage, and VAR support applications.

With our patented Dynamic Transfer™ feature, the MPS-125 inverter monitors grid stability and will automatically disconnect and transition to stand-alone mode if a grid disturbance is detected, ensuring consistent power to critical loads.



### Key Technologies

- Islanded Operation (UF Mode)
- Dynamic Transfer
- Black Start
- Frequency Compensation Mode (F-Comp)
- Volt-Var Compensation Mode (E-Comp)

## TECHNICAL SPECIFICATIONS

### Electrical

AC Input Voltage:	480V <sub>AC</sub> 3 Phase
Grid Frequency:	60 Hz
Rated Output Apparent Power:	125kVA
Rated Output Real Power:	125kW
Rated Output Current:	150A <sub>RMS</sub>
Overload AC Current:	180A <sub>RMS</sub>
DC Voltage Range:	740-1500V <sub>DC</sub>
Max DC Current:	171A <sub>DC</sub>
Power Factor:	0 – 1.00 Leading or Lagging
Current Harmonics:	IEEE 1547 Compliant, <5% TDD
Maximum Efficiency:	98.7%
CEC Efficiency:	97%

### Environmental & Mechanical

Operating Temp:	-25 to +50°C, De-rated from +45 to +50°C
Cooling:	Forced Air Cooled
Enclosure:	UL 3R/IP 54
Max Elevation:	1000 Meters Full Power Up to 3000 Meters with Derating
Dimensions (H x W x D):	42.5" x 29.5" x 15.5"
Weight:	230 lbs

### Certifications & Standards Compliance

UL 1741 Ed. 3	IEEE 519
IEEE 1547	CSA 22.2 #107.1
NFPA 70	

### Hardware Protections

AC Breaker with Shunt Trip
AC Surge Protection
DC Disconnect
DC Input Fuses
DC Pre-charge (Optional)

### Software Protections

Battery Voltage and Current Curtail Limits to Protect Battery
AC Current Limiting Pending
DC Over/Under Voltage, Over Current Faults
AC Over/Under Voltage, Over/Under Frequency, Over Current Faults
Anti-islanding Protection (Open Phase at inverter terminals)
Temperature Monitoring and Protective Power Curtailment
Watchdog Timer to Detect Loss of Communications



Datasheets provided by Sensata Technologies, Inc., its subsidiaries and/or affiliates ("Sensata") are solely intended to assist third parties ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, valuation, and judgment in designing Buyer's systems and products. Sensata datasheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular datasheet. Sensata may make corrections, enhancements, improvements, and other changes to its datasheets or components without notice.

Buyers are authorized to use Sensata datasheets with the Sensata component(s) identified in each particular datasheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATASHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATASHEETS OR USE OF THE DATASHEETS, EXPRESS, IMPLIED, OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATASHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at [www.sensata.com](http://www.sensata.com). SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY, AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA. Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA



#### REGIONAL HEAD OFFICES

##### United States of America

Sensata Technologies  
Attleboro, MA  
**Phone:** 508-236-3800  
**E-mail:** [support@sensata.com](mailto:support@sensata.com)

##### Netherlands

Sensata Technologies Holland B.V.  
Hengelo  
**Phone:** +31 74 357 8000  
**E-mail:** [support@sensata.com](mailto:support@sensata.com)

##### China

Sensata Technologies China Co., Ltd.  
Shanghai  
**Phone:** +8621 2306 1500  
**E-mail:** [support@sensata.com](mailto:support@sensata.com)

Copyright © 2023  
Sensata Technologies, Inc.



85 Meadowland Drive, South Burlington, Vermont USA 05403

**1.802.860.7200** | [sales@dynapower.com](mailto:sales@dynapower.com)

[dynapower.com](http://dynapower.com)

